

18W 2D bulkhead

Data Sheet

For Series: OT-OPB96



OTC IND CO., LTD

TEL: 0086-575-82913009 | Website: www.otcenterprise.com | Email: info@otcind.net



Dear partners,

* Thanks for choosing OTC LED bulkheads for your projects.

OTC always pursue high quality, steady quality products, competitive price and one-stop customer service, and offer enjoyable installation experience.

* All the OTC bulkheads with 5 years quality guarantee (Battery 3 years) . If any doubts/ questions, please contact OTC project support team directly by email support@otcind.net . You will get solutions in 7~24 hours rapidly.

Contents

1 Security realte information	2
2 Packing list	2
3 Basic Parameters	3
4 Sensor information/ setting	4
5 Typical sensor setting	5
6 Smart ambient light analyze	6
7 Installation guide	7

1 Security relate information

- Installation should be carried out in accordance with the latest edition of the I.E.E. Wiring regulations and taking into consideration the latest building regulations.
- Ensure that all electrical connections are tight with no loose strands, including factory made connections.
- Ensure there is adequate free air circulation of at least 100mm around the luminaire. It is the installer's responsibility to consider fire risk and take appropriate precautions.
- A seperate enclosure may be required if this unit is to be used in dusty and wet environments.

Q.C. date label, installation in an improper working environment or installation not according to the current edition of the I.E.E. Wiring Regulations . The guarantee is also invalidated if the luminaire has been I.R. tested. Should this product fail during the guarantee period it will be replaced free of charge, subject to correct installation and return of the faulty unit. We do not accept responsibility for any installation costs associated with the replacement of this product. Your statutory rights are not affected. We reserve the right to alter specifications without prior notice.

2 Packing list



The Lamp *1




Installation pack *1




User manual *1

3 Basic Parameters

Model	Art Nr. OT-OPB-***	
	96	96MC
Material	100% PC case	
Dimension	D320*H75mm	
LED Chips	96 SMD 2835	
Color Rendering Index	>80	
Degree of protection	IP65 / IK09	
CCT	3000, 4000 or 6000K	
Input Voltage	AC200-240V 50/60HZ	
Input power	18W	18W
Power factor	>0.9	>0.9
Luminous Flux(Mains)	1700Lm	
LED lifespan	50,000 hrs	
↓ Next are sensor parameters ↓		
Microwave Sensor	NO sensor	Yes
Frequency		5.8GHZ
Detection range		10m
Lux detector		10/20/30/Disable
Delay time		10S~10min
Corridor function		With
Ambient light detect		With (See page 6)



H75mm



D320mm

4 Sensor information/ Setting (96MC only)

Technical Data	
Operating Voltage	20-60VDC
Input current	100mA (Min.)~1300mA (Max.)
Switched power	Max. 60W
Standby power	<0.5W
Detection Range	25/50/75/100% , optional by dial swith
Daylight threshold	10~50Lux, disabled, optional by dial switch
Hold time	10s/1min/6min/12min, optional by dial switch
Standby period	1min/30min/60min/24H, optional by dial switch
Standby Dimming level	10/20/30, disabled, optional by dial switch
Microwave frequency	5.8GHz ±75MHz
Max detection Range	20Metres
Detection angle	360°
Mounting height	Max. 4m
Operating temperature	-35°C~70°C
Microwave power	<0.2mW (that is just one 5000th of the transmission power of a mobile phone)

Microwave sensor setting



Dial switch setting

1. Detection Range Setting

1	2	Distance	1	2	Distance
<input type="checkbox"/>	<input type="checkbox"/>	25%	<input type="checkbox"/>	<input type="checkbox"/>	50%
<input type="checkbox"/>	<input type="checkbox"/>	75%	<input type="checkbox"/>	<input type="checkbox"/>	100%

2. Hold Time setting

3	4	Time	3	4	Time
<input type="checkbox"/>	<input type="checkbox"/>	10S	<input type="checkbox"/>	<input type="checkbox"/>	1Min
<input type="checkbox"/>	<input type="checkbox"/>	5Min	<input type="checkbox"/>	<input type="checkbox"/>	10Min

3. Daylight threshold setting



5	6	Light	5	6	Light
<input type="checkbox"/>	<input type="checkbox"/>	Day	<input type="checkbox"/>	<input type="checkbox"/>	10Lux
<input type="checkbox"/>	<input type="checkbox"/>	30Lux	<input type="checkbox"/>	<input type="checkbox"/>	50Lux

4. Standby dim level setting

7	8	CF	7	8	CF
<input type="checkbox"/>	<input type="checkbox"/>	0%	<input type="checkbox"/>	<input type="checkbox"/>	10%
<input type="checkbox"/>	<input type="checkbox"/>	20%	<input type="checkbox"/>	<input type="checkbox"/>	30%

5. Standby period setting


9	10	CF Holding	9	10	CF Holding
<input type="checkbox"/>	<input type="checkbox"/>	24H	<input type="checkbox"/>	<input type="checkbox"/>	1Min
<input type="checkbox"/>	<input type="checkbox"/>	30Min	<input type="checkbox"/>	<input type="checkbox"/>	60Min




Detection Range

5 Typical sensor setting (96MC only)


1-ON-OFF function



1 - With sufficient ambient light, the light will not switch on, even if the motion sensor is triggered




2 - with insufficient ambient light, the light is switched on when motion is detected




3 - when no motion is detected, the light switches off after the hold-time has passed **The holding time is controlled by 3 & 4.**


2- step dimming function (Corridor function)




1- The low level will activate automatically if insufficient ambient light, despite no motion is detected.
10/ 20%/ 30% available by dip switch 7 & 8. It is 20% in this case



2- when motion is detected. The light brightness to 100%




3- when no motion is detected. The light dims to the set low level after the hold-time has passed.
Hold-time set by 3 & 4. 1 minutes in this case




4- The Low level will cut off, if sufficient ambient light. No matter the motion detected or not. (Smart sun-light detection)
9 & 10 set to 24H


3- step dimming function




1 - With sufficient ambient light, the light will not switch on, even if the motion sensor is triggered



2 - with insufficient ambient light, the light is switched on when motion is detected



3 - when no motion is detected, the light dims to the set low light level after the hold-time has passed.
10/ 20%/ 30% available by dip switch 7 & 8. It is 20% in this case





4 - when no motion is detected, the light turns off after the standby-period has passed.
The holding time controlled by 9 & 10. It is 30mins in this case.

5 Smart ambient light analyze




This microwave sensor embed
Smart ambient light analyze sensor

1- Why the world need ambient light analyze



The Lux control of Tradiation motion sensor only can control turn on.

In a) if insufficient ambient light at 5:00am, it will sensor on if motion detected. However, if stream of people go through the corridor constantly b), The Lux sensor can not cut off the lamp, despite of sufficient ambient light (10:00am).



Once active the corridor function c). The lux sensor will useless, The light will on no matter in Day or night if motion detected d) .

2- What it will be if you chose smart ambient analyze sensor



Once the sufficient ambient light was detected, The luminaire will be certain in OFF mode for energy saving.


6 Installation guide

1. All OTC LED bulkheads are designed for projects. Only qualified electrician can install or maintain it.
2. The mains have to be off during the installation or maintenance.
3. Keep the product far from heat sources and in a well ventilated area.




Caution

Installation




1. Make sure the Mains OFF
2. Drill the install hole on the wall.
3. Nail the Alligator into the hole .
4. Make the AC power cable through the waterproof rubber access cap.
5. Fix the Base to the wall by screws and Aluminium washer.

STEP 1




1. Connect the AC cable to the LED PCB

STEP 2



1. Install the LED Gear Tray
2. Fix the LED Gear Tray by screw driver
3. Set the sensor according to the usermanual

STEP 3



1. Install the Diffuser
2. Install the Decoration trim(Optional).
3. Finally, mains on to test the bulkhead again

STEP 4